Step 1: Scan and download the app from the QC code on the outside of the box.

Step 2: Plug in the Wi-Fi box to a 5V USB power source (either a computer, a dedicated USB jack or even a cell phone USB input charger will work.

3:45 3:45 🖻 0 🛯 📲 🛸 🖉 26% 🛔 0 10 41 34 41 26% O 0 0 Add Device **Energy Saving Energy Saving** 1111-1 Create Scene E Scan No devices No devices Add Device Add Device 0 0 \checkmark 0 0 2 6 0 THERE THERE State Mil Home State NN Home 111 0 111 ζ. ζ.

Step 3: Click on the + "Add Device" after loading up the app. See below:

Step 4: Click on "2.4G Gateway at the top left corner of your screen. Before doing so, make sure your phone is next to the Wi-Fi box for best transmission and synching. It will then prompt you to log into your Wi-Fi. Wait approx. 15-30 seconds while it adds your Wi-Fi Box, and when successful you will see "2.4G Gateway Added Successfully". Click on "Done", and it will bring you to a black screen with a color palette wheel.

345 🖬	0 4 4	15 A 20% E	345 🖬	0 8 4 % ± 20% 1	3.46 🖬	0	# 4 % / 20% L	3.46 🖬		0 # 4 % / 20% L
<	Add Device	8		×	×	Add Device		×	Add Device	
 Sensing to easily prime. Man was per branches without a true with. 			Enter Wi-Fi In Chesos III Plants	formation	T-Monte and				14	
0	1		♥ withwite	<i></i>	91	G Catevia e =====		2.40	Sahaway	<i>v</i>
interes)		A magnit					-	ii.	
	Add Manually									
Electrical	Socket									
Lighting		1.1								
-	WD-will livid	(Calma)								
i arga berter Agamenti Mana berter	and construction	14 Antonio Antonio		***)				-(-	
		<	Ш	0 <		0	<		0	<

Step 5: At the bottom left of the screen you will see a "Choose Zone". It will be at "All", change it to Zone 1. Repeat the below for different zones "Zone 2, 3, etc.) if you wish to separate lights on different zones. If not, all you need is Zone 1.



Step 6: At the top right of the screen, you will see "Set" as an option. Click on "Set".



Step 7: Power off your color-changing lights completely for about 10 seconds, then power the lights on, and within 3 seconds of powering the lights on, click on the big green "Link" button. If successfully linked, the lights will flash green then go back to red, and you're good to go!

3:47 🖪		a 🗴 💐 🗟 📲 26% 🗖					
<	2.4G Gat	eway		<u>/</u>			
White 0	Color	Mode		Set			
ی Do not distur	b mode	? C	pen	Close			
≈ Switch frequ	ence	?	ligh	Low			
B Default mode	e	?		2			
슈 Gateway Indic	ator			On >			
ିମ୍ବ Copy remote							
 Link/Unlink Control light a 				0			
Link		U	alink				
			+				
Choose zone Zone 1	ON	OFF		0			
	0		<				

Please note: If you wish to unlink the lights, repeat Step 7 for said specified zone and hit the red "Unlink" button instead.